

GlobalLux

LIGHTING

14" LED DECORATIVE CEILING FIXTURE

DIRECT WIRE - QUICK AND EASY TO INSTALL

ASSEMBLY INSTRUCTIONS

1. Preparing for Installation

A. Disconnect electrical power at fuse or circuit breaker box before installing or servicing any part of this fixture.

B. Remove fixture and hardware bag from cartoning.

2. Wiring

All wiring must take place inside

junction box. Caution: Make sure power is off at fuse or circuit breaker box. Check power wires for damage or scrapes. If power supply wires are within three inches of ballast use wire suitable for at least 90C (194F).

Note: Most dwellings built before 1985 have supply wire rated to 60C. Consult a qualified electrician before installing.

A. This unit will not operate properly unless connected to a "grounded" electrical circuit. Electrical shock, over heating, low or no light output, and shortened lamp life can result if proper grounding is not done. Securely attach green (or green and yellow) wire to ground supply wire.

B. Using wire connectors (provided), connect white supply wire to white ballast lead. Connect black hot supply wire to black ballast lead. Do not mix wires.

Pull on each wire lead to make sure connections are secure. Make certain no bare wires are exposed outside of wire connectors.

3. Mounting

Thread canopy screws into mounting cross bar few full turns (To be tightened later).

Fasten mounting strip onto outlet box using another 2 mounting screws (provided).

Place canopy on mounting strip, Let the heads of the canopy mounting screws come out of the keyhole slots in the canopy face. Twist the ceiling canopy until the heads of the canopy screws are in the narrow end of the keyhole slots. Fully tighten the screws to secure the canopy to the ceiling.

4. Lamps

To install, place a 17W LED ring on the canopy, press 3 plastic rivets provided to tighten the ring, connect the driver and LED by plug the driver wire into the terminal on the LED ring.

5. Diffuser Mounting

Place diffuser on the canopy, twist clockwise until knock into place.

6. Power to the fixture can now be restored

7. LED driver is replaceable. Please contact customer service for ordering information.

